

IR Emitter and Detector Product Data Sheet

> **LTE-C9306 Spec No.: DS50-2007-0010** Effective Date: 04/20/2007 Revision: -



BNS-OD-FC001/A4

LITE-ON Technology Corp. / Optoelectronics No.90,Chien 1 Road, Chung Ho, New Taipei City 23585, Taiwan, R.O.C. Tel: 886-2-2222-6181 Fax: 886-2-2221-1948 / 886-2-2221-0660 http://www.liteon.com/opto



Property of Lite-On Only

### FEATURES

- \* MEET ROHS, GREEN PRODUCT.
- \* PACKAGE IN 8MM TAPE ON 7" DIAMETER REELS.
- \* COMPATIBLE WITH INFRARED AND SOLDER PROCESS.
- \* EIA STD PACKAGE.

### **PACKAGE DIMENSIONS**



- 2. Tolerance is  $\pm$  0.1 mm (.004") unless otherwise noted.
- 3. Specifications are subject to change without notice.

Part No. :	LTE-C9306 DATA SHEET
1 unt 1 10	LIL C/300 DATA SHLLI

Page: 1 of

7



Property of Lite-On Only

### ABSOLUTE MAXIMUM RATINGS AT TA=25℃

PARAMETER	MAXIMUM RATING	UNIT	
Power Dissipation	75	mW	
Peak Forward Current (300pps, $10 \mu$ s pulse)	500	mA	
Continuous Forward Current	50	mA	
Reverse Voltage	5	V	
Operating Temperature Range	$-25^{\circ}\text{C}$ to $+85^{\circ}\text{C}$		
Storage Temperature Range	$-55^{\circ}$ C to $+85^{\circ}$ C		
Wave Soldering Condition	260°C for 5 Seconds		
Infrared Reflow Condition	260°C for 5 Seconds		

Suggestion IR Reflow Profile For Pb Free Process



Property of Lite-On Only

### ELECTRICAL / OPTICAL CHARACTERISTICS AT TA=25°C

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	TEST CONDITION
Radiant Intensity	I <sub>E</sub>	4	9	-	mW/sr	$I_F = 20 m A$
Radiant Intensity	I <sub>E</sub>	10	22.5	-	mW/sr	$I_F = 50 mA$
Peak Emission Wavelength	$\lambda_{Peak}$	-	850	-	nm	$I_F = 20 m A$
Spectral Line Half-Width	Δλ	-	50	-	nm	$I_F = 20 m A$
Forward Voltage	V <sub>F</sub>	1.3	1.45	1.65	V	$I_F = 20 mA$
Reverse Current	I <sub>R</sub>	-	-	10	μΑ	$V_R = 5V$
Rise/Fall Time	Tr/Tf	-	30	-	nS	$10\% \sim 90\%$ , $I_F = 20mA$
Viewing Angle (See FIG.6)	$2\theta_{1/2}$	-	20	-	deg.	

Part No. : LTE-C9306 DATA SHEET



Property of Lite-On Only





Property of Lite-On Only

### **CLEANING:**

Do not use unspecified chemical liquid to clean LED they could harm the package. If clean is necessary, immerse the LED in ethyl alcohol or in isopropyl alcohol at normal temperature for less one minute.

### SUGGEST SOLDERING PAD DIMENSIONS



### PACKAGE DIMENSIONS OF TAPE AND REEL





Property of Lite-On Only



# LITEON

## LITE-ON TECHNOLOGY CORPORATION.

Property of Lite-On Only

### CAUTIONS

### **1. APPLICATION**

The LEDs described here are intended to be used for ordinary electronic equipment (such as office equipment, communication equipment and household applications).Consult Liteon's Sales in advance for information on applications in which exceptional reliability is required, particularly when the failure or malfunction of the LEDs may directly jeopardize life or health (such as in aviation, transportation, traffic control equipment, medical and life support systems and safety devices).

#### 2. STORAGE

The storage ambient for the LEDs should not exceed 30°C temperature or 70% relative humidity. It is recommended that LEDs out of their original packaging are IR-reflowed within one week. For extended storage out of their original packaging, it is recommended that the LEDs be stored in a sealed container with appropriate desiccant, or in a desiccators with nitrogen ambient. LEDs stored out of their original packaging for more than a week should be baked at about 60 deg C for at least 24 hours before solder assembly.

#### **3. CLEANING**

Use alcohol-based cleaning solvents such as isopropyl alcohol to clean the LED if necessary.

### 4. SOLDERING

Recommended soldering conditions:

Reflow soldering		Wave So	ldering	Soldering iron		
Pre-heat	120~150°C	Pre-heat	100°C Max.	Temperature	300°C Max.	
Pre-heat time	120 sec. Max.	Pre-heat time	60 sec. Max.	Soldering time	3 sec. Max.	
Peak temperature	240°C Max.	Solder wave	260°C Max.	_	(one time only)	
Soldering time	10 sec. Max.	Soldering time	10 sec. Max.			

### **5. DRIVE METHOD**

An LED is a current-operated device. In order to ensure intensity uniformity on multiple LEDs connected in parallel in an application, it is recommended that a current limiting resistor be incorporated in the drive circuit, in series with each LED as shown in Circuit A below.



Circuit model B



(A) Recommended circuit.

(B) The brightness of each LED might appear different due to the differences in the I-V characteristics of those LEDs.

#### 6. OTHERS

The appearance and specifications of the product may be modified for improvement without prior notice.

Part No. : LTE-C9306 DATA SHEET	Page :	7	of	7	
---------------------------------	--------	---	----	---	--